

ENVIRONMENTAL DUSTTRAK™ ENVIRONMENTAL ENCLOSURE MODEL 854030

(FOR ENVIRONMENTAL DUSTTRAK™ AND DRX AEROSOL MONITOR
MODELS 8540, 8540-M, 8542-M, 8543, AND 8543-M)

OPERATION AND MAINTENANCE MANUAL

P/N 6008410, REVISION F
NOVEMBER 2016



START SEEING THE BENEFITS OF REGISTERING TODAY!

Thank you for your TSI instrument purchase. Occasionally, TSI releases information on software updates, product enhancements and new products. By registering your instrument, TSI will be able to send this important information to you.

<http://register.tsi.com>

As part of the registration process, you will be asked for your comments on TSI products and services. TSI's customer feedback program gives customers like you a way to tell us how we are doing.



UNDERSTANDING, ACCELERATED

TSI Incorporated - Visit our website **www.tsi.com** for more information.

USA
UK
France
Germany

Tel: +1 800 874 2811
Tel: +44 149 4 459200
Tel: +33 1 41 19 21 99
Tel: +49 241 523030

India
China
Singapore

Tel: +91 80 67877200
Tel: +86 10 8219 7688
Tel: +65 6595 6388

©2015 TSI Incorporated

Printed in U.S.A.

Copyright©

TSI Incorporated / 2015-2016 / All rights reserved.

Part Number

6008410 / Revision F / November 2016

Address

TSI Incorporated / 500 Cardigan Road / Shoreview, MN 55126 / USA

Fax No.

(651) 490-3824

LIMITATION OF WARRANTY AND LIABILITY (effective February 2015)

(For country-specific terms and conditions outside of the USA, please visit www.tsi.com.)

Seller warrants the goods, excluding software sold hereunder, under normal use and service as described in the operator's manual, shall be free from defects in workmanship and material for twenty-four (24) months, or if less, the length of time specified in the operator's manual, from the date of shipment to the customer. This warranty period is inclusive of any statutory warranty. This limited warranty is subject to the following exclusions and exceptions:

- a. Hot-wire or hot-film sensors used with research anemometers, and certain other components when indicated in specifications, are warranted for 90 days from the date of shipment;
- b. Environmental DustTrak pump for Models 8540, 8540-M, 8542-M, 8543, and 8543-M is warranted for two (2) years or 8760 hours, whichever comes first.
- c. Parts repaired or replaced as a result of repair services are warranted to be free from defects in workmanship and material, under normal use, for 90 days from the date of shipment;
- d. Seller does not provide any warranty on finished goods manufactured by others or on any fuses, batteries or other consumable materials. Only the original manufacturer's warranty applies;
- e. This warranty does not cover calibration requirements, and seller warrants only that the instrument or product is properly calibrated at the time of its manufacture. Instruments returned for calibration are not covered by this warranty;
- f. This warranty is **VOID** if the instrument is opened by anyone other than a factory authorized service center with the one exception where requirements set forth in the manual allow an operator to replace consumables or perform recommended cleaning;
- g. This warranty is **VOID** if the product has been misused, neglected, subjected to accidental or intentional damage, or is not properly installed, maintained, or cleaned according to the requirements of the manual. Unless specifically authorized in a separate writing by Seller, Seller makes no warranty with respect to, and shall have no liability in connection with, goods which are incorporated into other products or equipment, or which are modified by any person other than Seller.

The foregoing is **IN LIEU OF** all other warranties and is subject to the **LIMITATIONS** stated herein. **NO OTHER EXPRESS OR IMPLIED WARRANTY OF FITNESS FOR PARTICULAR PURPOSE OR MERCHANTABILITY IS MADE. WITH RESPECT TO SELLER'S BREACH OF THE IMPLIED WARRANTY AGAINST INFRINGEMENT, SAID WARRANTY IS LIMITED TO CLAIMS OF DIRECT INFRINGEMENT AND EXCLUDES CLAIMS OF CONTRIBUTORY OR INDUCED INFRINGEMENTS. BUYER'S EXCLUSIVE REMEDY SHALL BE THE RETURN OF THE PURCHASE PRICE DISCOUNTED FOR REASONABLE WEAR AND TEAR OR AT SELLER'S OPTION REPLACEMENT OF THE GOODS WITH NON-INFRINGEMENTS GOODS.**

TO THE EXTENT PERMITTED BY LAW, THE EXCLUSIVE REMEDY OF THE USER OR BUYER, AND THE LIMIT OF SELLER'S LIABILITY FOR ANY AND ALL LOSSES, INJURIES, OR DAMAGES CONCERNING THE GOODS (INCLUDING CLAIMS BASED

ON CONTRACT, NEGLIGENCE, TORT, STRICT LIABILITY OR OTHERWISE) SHALL BE THE RETURN OF GOODS TO SELLER AND THE REFUND OF THE PURCHASE PRICE, OR, AT THE OPTION OF SELLER, THE REPAIR OR REPLACEMENT OF THE GOODS. IN THE CASE OF SOFTWARE, SELLER WILL REPAIR OR REPLACE DEFECTIVE SOFTWARE OR IF UNABLE TO DO SO, WILL REFUND THE PURCHASE PRICE OF THE SOFTWARE. IN NO EVENT SHALL SELLER BE LIABLE FOR LOST PROFITS, BUSINESS INTERRUPTION, OR ANY SPECIAL, INDIRECT, CONSEQUENTIAL OR INCIDENTAL DAMAGES. SELLER SHALL NOT BE RESPONSIBLE FOR INSTALLATION, DISMANTLING OR REINSTALLATION COSTS OR CHARGES. No Action, regardless of form, may be brought against Seller more than 12 months after a cause of action has accrued. The goods returned under warranty to Seller's factory shall be at Buyer's risk of loss, and will be returned, if at all, at Seller's risk of loss.

Buyer and all users are deemed to have accepted this LIMITATION OF WARRANTY AND LIABILITY, which contains the complete and exclusive limited warranty of Seller. This LIMITATION OF WARRANTY AND LIABILITY may not be amended, modified or its terms waived, except by writing signed by an Officer of Seller.

Service Policy

Knowing that inoperative or defective instruments are as detrimental to TSI as they are to our customers, our service policy is designed to give prompt attention to any problems. If any malfunction is discovered, please contact your nearest sales office or representative, or call TSI's Customer Service department at (800) 874-2811 (USA) or (001 651) 490-2811 (International) or visit www.tsi.com.

Trademarks

DustTrak and TrakPro are trademarks of TSI Incorporated. Netronix is a trademark of Netronix Inc. Velcro is a registered trademark of Velcro Industries B.V. Teflon is a registered trademark of DuPont.

Contents

Contents	iii
Safety Information	v
Laser Safety	vi
Labels	vii
Description of Caution/Warning Symbols	vii
Caution and Warning Symbols	viii
Reusing and Recycling	viii
Chapter 1 Product Overview	1
Chapter 2 Parts Identification and Unpacking	3
Parts Identification: Environmental Enclosure	3
Unpacking the Model 854030 Environmental Enclosure	3
Model 854030 Environmental Enclosure Optional Accessories.....	5
Chapter 3 Setting Up	9
Enclosure Assembly	9
Tools Needed for Assembly.....	9
Equipment Needed for Maintenance	9
Overview	10
Cable Routing and Securing.....	10
Install Photometer.....	10
Solar Shield	12
Thiamis 1000 Node	12
Configure Power Connection.....	13
DIN Rail and Phoenix Connectors	14
Mains Power Supply for Environmental DustTrak	15
Environmental DustTrak Battery Kit.....	16
Alternate DC Power Sources.....	18
Heated Inlet Accessory.....	18
Enclosure Heater.....	19
Install Photometer inside Environmental Enclosure.....	20
Assembly and Installation of Inlet Column	21
Pole Mount Kit	24
Final Electrical Connection	24

Chapter 4 Operation.....	27
Overview	27
How to Properly Orient the Environmental Enclosure	27
Checklist for Sampling with the Environmental Enclosure.....	28
Transporting the Environmental Enclosure	28
Removing Photometer from Environmental Enclosure for Service or Replacement	29
Re-installing the Inlet Assembly	35
Chapter 5 Maintenance	39
Annual Maintenance Checks.....	39
Cleaning the Aerosol Inlet	40
Emptying the Water Trap	40
Cleaning and Oiling Impactors	41
Chapter 6 Troubleshooting the Environmental Enclosure	43
Appendix A Specifications.....	45
Environment Enclosure	45

Safety Information



WARNINGS

- The DustTrak™ 8540/8540-M/8542-M/8543/8543-M aerosol monitors are not rated for intrinsic safety. The DustTrak monitor, with the Environmental Enclosure, must **never** be operated under conditions where there is a risk of fire or explosion.
- Use of components other than those specified by TSI may impair the safety features provided by the equipment.
- The instrument has been design to be used with batteries supplied by TSI. Do **not** use a substitute.

The TSI charger (P/N 801809) has been designed to be used with the battery packs supplied by TSI. Do **not** use a substitute charger to charge TSI battery packs.

Old batteries must be properly recycled in accordance with the local environmental regulations.
- When mains power adapters are used, the equipment should be positioned so the mains plug will remain accessible for emergency disconnect.
- Do **not** use non-rechargeable batteries in this instrument. Fire, explosions, or other hazards may result.



Cautions

- The enclosure is designed to be water resistant to rain or spray. It has a NEMA rating of 3R and an ingress protection rating of IP44. It is not designed to be waterproof when immersed. Setting it in a pool of water will result in flooding the inner compartment with water. This will severely damage both your DustTrak/DRX aerosol monitor and battery pack. **DO NOT** set the Environmental Enclosure in **water!**
- Any seal that is not properly installed could result in water intrusion inside the enclosure which can damage the instruments and batteries. Follow procedures outlined in this manual for proper installation and regular inspection of all seals.

Note

Prior to using the Battery Pack for the first time, a full recharge is recommended. **Recharging Battery Pack(s) immediately after use (within one hour maximum) is critical to obtaining optimal recharge time, battery health, and battery life.**

Laser Safety

- Models 8540/8540-M/8542-M/8543/8543-M DustTrak monitors are Class I laser-based instruments.
- During normal operation, you will **not** be exposed to laser radiation.
- Precaution should be taken to avoid exposure to hazardous radiation in the form of intense, focused, visible light.
- Exposure to this light may cause blindness.

Take these precautions:

- **DO NOT** remove any parts from the DustTrak monitor unless you are specifically told to do so in this manual.
- **DO NOT** remove the housing or covers. There are no serviceable components inside the housing.



WARNING

The use of controls, adjustments, or procedures other than those specified in this manual may result in exposure to hazardous optical radiation.



WARNING

If the DustTrak monitor is used in a manner not specified by the manufacturer, the protection provided by the equipment may be impaired.

When operated according to the manufacturer's instruction, this device is a Class I laser product as defined by U.S. Department of Health and Human Services standards under the Radiation Control for Health and Safety Act of 1968. A certification and identification label like the one shown below is affixed to each instrument.

Labels

Advisory labels and identification labels are attached to the instrument.

1. European symbol for non-disposable item. Item must be recycled.



Description of Caution/Warning Symbols

Appropriate caution/warning statements are used throughout the manual and on the instrument that require you to take cautionary measures when working with the instrument.

Caution



Caution

Failure to follow the procedures prescribed in this manual might result in irreparable equipment damage. Important information about the operation and maintenance of this instrument is included in this manual.

Warning



WARNING

Warning means that unsafe use of the instrument could result in serious injury to you or cause damage to the instrument. Follow the procedures prescribed.

Caution and Warning Symbols



The following symbols may accompany cautions and warnings to indicate the nature and consequences of hazards:

	Warns that the instrument contains a laser and that important information about its safe operation and maintenance is included in the manual.
	Warns that the instrument is susceptible to electrostatic discharge (ESD) and ESD protection should be followed to avoid damage.
	Indicates the connector is connected to earth ground and cabinet ground.

Reusing and Recycling



As part of TSI Incorporated's effort to have a minimal negative impact on the communities in which its products are manufactured and used:

-  Do **not** dispose of used batteries in the trash. Follow local environmental requirements for battery recycling.
-  If instrument becomes obsolete, return to TSI for disassembly and recycling.

Chapter 1

Product Overview

The environmental enclosure allows for protection of the Environmental DustTrak Models 8540/8540-M/8542-M/8543/8543-M and their accessories to permit outdoor monitoring.



Figure 1: Open Enclosure with a large flat head screwdriver by turning latch ¼ turn



Figure 2: Front view of open enclosure




Figure 3: Power Strip

Chapter 2

Parts Identification and Unpacking



Carefully unpack the Model 854030 Environmental DustTrak™ Environmental Enclosure from the shipping container. Use the tables and illustrations below to make certain that there are no missing components. Contact TSI immediately if anything is missing or damaged.

Parts Identification: Environmental Enclosure



Identify the parts of the Model 854030 DustTrak Aerosol Monitor Environmental Enclosure (see unpacking list below). Please become familiar with these components before proceeding.

Unpacking the Model 854030 Environmental Enclosure

Compare all the components you received with those listed in the table below. If any parts are missing, contact TSI.






Item	Qty	Part Number	Description
Spare Parts available from suppliers by manufacturer part number listed below			
 www.phoenixcontact.com	4	Spring cage ground terminal block (Green)	Power Connector Ground (Green)
		Large – P/N 3042733	(1) large – incoming power
		Small – P/N 304002	(3) small – power distribution
 www.phoenixcontact.com	4	Feed-through terminal block (Gray)	Power Connector Supply (Gray)
		Large – P/N 3042719	(1) large – incoming power
		Small – P/N 3040012	(3) small – power distribution

Item	Qty	Part Number	Description
 <p>www.phoenixcontact.com</p>	3	Plug-in Bridge	Power Jumper
		Large, 22.7 mm x 9 mm, two-position P/N 3030161	(1) large – incoming power to distribution terminal blocks
		Small, 22.7 mm x 14.2 mm, three-position P/N 3030174	(2) small – to connect terminal block to terminal block
 <p>https://octopart.com/</p>	11	Small plug Heyco® Nylon 0.5" dia Hole Plug, KOS LT 500 P/N 3830	Plug for 0.5" holes for handle bolts and wireless antenna
	1	Washer, ½ INT tooth lock 7/8 OD ZN	Tooth lock washer to hold antenna plug in place
 <p>https://octopart.com/</p>	4	Large Plug Heyco® -molded break-thru plug, 1.093" dia, LTGP 1093-063 P/N C2024	Plug for 1.093" holes for power and communication connections
 <p>https://octopart.com/</p>	2	Cable Gland Heyco® Series-35 liquid tight cord grips, LTF ¾, P/N 3234	Creates weather-proof seal for cable penetrations
 <p>https://octopart.com/</p>	2	Jam nut for cable gland Heyco® Nylon Locknuts, NLN ¾ NPT P/N 8465	Secures cable gland to enclosure.



Item	Qty	Part Number	Description
	1	1' USB Cable	Connects Photometer to Environmental Enclosure USB Connector
	1	Power Cable to Photometer	Connects DIN Rail 12V Supply to Photometer

Model 854030 Environmental Enclosure Optional Accessories

Listed below are optional accessory items for the Model 854030 Environmental Enclosure. Contact TSI for purchase info.

Item	Part Number	Description
	854031	Pole Mount Kit for 854030 Enclosure
	854032	Solar Shield for 854030 Enclosure
	854033	Enclosure Heater for 854030 Enclosure
	854034	Power supply for Environmental DustTrak
	854041	Heated Inlet Sample Conditioner

Item	Part Number	Description
	801905	Thiamis 1000 GSM/GPS Node
	854020	PM ₁₀ Impactor
	854021	PM _{2.5} Impactor
	854022	PM _{1.0} Impactor
	854050	Lufft WS300 Metrology Station (Temp, Rh, air pressure)
	854051	Lufft WS500 Metrology Station (Temp, Rh, air pressure, wind speed, wind direction)
	854060	Solar Power System
	854036	Internal Battery System: Two (2) 22Ah Batteries* (801808), charger** (801809), plastic tray, and custom cable.

Item	Part Number	Description
	801808*	12 VDC Battery Pack*
	801809**	12 VDC Battery Pack Charger

(This page intentionally left blank)

Chapter 3

Setting Up

The setup of the Environmental Enclosure is important to reliable and accurate sampling of aerosols in a wide range of conditions. TSI cannot ensure accurate measurements if any of the components are set up incorrectly. Failure to follow these procedures could result in damage to the enclosure or its components.

Enclosure Assembly

These assembly steps are organized to incorporate all available optional accessories at the time of assembly. Optional accessories can easily be added after assembly; however, some components may need to be temporarily removed to facilitate installation and connection of some accessories.

Tools Needed for Assembly

(varies by accessory)

- Large flat-blade screwdriver
- Small flat-blade screwdriver
- Medium Phillips screwdriver
- $\frac{5}{16}$ " wrench
- $\frac{3}{8}$ " wrench
- $\frac{1}{2}$ " wrench or socket
- $\frac{9}{16}$ " wrench
- $\frac{9}{16}$ " deep well socket
- $\frac{5}{32}$ " ball driver or Allen wrench

Equipment Needed for Maintenance

- Compressed air or canned compressed air
- Teflon[®] pipe tape

Overview

The manual follows the order of the steps listed below with reference to applicable Quick Start Guides for optional accessories.

1. Start by opening door using large flat blade screw driver to turn latch $\frac{1}{4}$ turn.
2. Install Thiamis Node antenna (use extender if solar shield will be installed).
3. Install solar shield (optional accessory).
4. Install RH/Temp. Sensor if Heated Inlet Sample Conditioner module will be used (optional accessory).
5. Connect internal power supply connections (AC Power Supply, DC Power Connection Battery or Solar).
6. Connect heater, thermostat, and phoenix connector for Enclosure Heater (optional accessory) to DIN rail.
7. Install Thiamis Node on photometer service panel.
8. Install Heated Inlet Control Module (optional accessory) on photometer.

Cable Routing and Securing

Adhesive backed cable tie anchors are provided to help secure cables inside the enclosure. Securing cables to specific locations on the photometer and enclosure can prevent damage to cables during installation and removal of the photometer and help reduce confusion and mistakes during set up.

Securing the cables to the enclosure is much easier to accomplish before the various accessories and photometer are mounted in the enclosure. Follow the Quick Start Guide steps included with the accessories for securing cables for any optional accessories to be used.

Install Photometer

1. Insert photometer into enclosure and secure with retaining ring.
2. Build inlet column with Heated Inlet Sample Conditioner (optional accessory), impactors (optional choice), water trap, and 360° omni-directional inlet.
3. Thread Heated Inlet Cable (optional accessory) through the slot opening on the bottom of the Mounting Ring.

4. Place inlet column on top of photometer ring and rotate until alignment pin engages. Tighten down column ring to secure inlet column to photometer.
5. Connect cables for Photometer, Netronix Node, and any optional accessories (Heated Inlet, Enclosure Heater) as directed in the Quick Start Guides.
6. Connect batteries or connect to external power source.
7. Handles install through the same holes with the same hardware used to attach the solar shield. The optional Solar Shield (854032) can be installed at the same time the handles are installed.




Figure 4: Install optional solar shield (854032)

Refer to the Quick Start Guides supplied with the optional accessories for installation instructions:

Solar Shield

(optional accessory P/N 854032)

See Quick Start Guide 6008675 included with accessory.



Figure 5: Solar shield (854032)

Thiamis 1000 Node

(optional accessory P/N 801905)

See Quick Start Guide 6008413 included with accessory.



Figure 6: Thiamis 1000 Node (801905)

Configure Power Connection

The 8540/8540-M/8542-M/8543/8543-M Environmental DustTrak may be powered with:

1. AC mains power (part number 854034)
2. Battery Pack Kit (part number 854036)
3. DC input for Solar Power (part number 854060).

The power connections and set up within the enclosure are much easier to manage before the photometer is installed. External connection to the power supply should not occur until the photometer and associated accessories are connected inside the enclosure.

Note

The power supply included with the Enclosure Heater Accessory (P/N 854033) requires AC Mains Power.

DIN Rail and Phoenix Connectors

Power supplied to the Instruments is fed through an assembly of Phoenix Connectors snapped onto the DIN rail. Additional Phoenix Connectors can be purchased directly from www.phoenixcontact.com.

- Green connectors are the “DC ground” connection.
- Gray connectors are the “positive DC voltage” connection.

The pair of larger connectors (size 4) on the far left bring power into the DIN rail from Main Line Power, Batteries, Solar Power System, or Wind Power system.

The smaller pairs of connectors (size 2.5) are used to supply power to various instruments in the enclosure. Additional connectors can be added to power additional instruments as needed.

All “power connectors” require a strong insertion force to fully seat the connector.

The red plug-in bridge clips distribute power from a Gray connector to the adjacent or the next Gray connector. Note the different sizes of red jumper clips.




Figure 7: DIN rail and Phoenix connectors

Replacement connectors can be purchased directly from the manufacturer as follows:

www.phoenixcontact.com

Connector	Part Number
Adjacent jumper (to distribute power from large gray connector to adjacent small gray connector)	3030161
Regular jumper (to distribute power from a small gray connector to another small gray connector)	3030174
Large, Incoming Power Connector:	
Green (DC ground)	3042722
Gray (positive DC voltage)	3042719
Small, Distribution Power Connectors:	
Green (DC Ground)	3040025
Gray (positive DC voltage)	3040012

Mains Power Supply for Environmental DustTrak

(optional accessory P/N 854034)

See Quick Start Guide 6008574 included with Power Supply.

Attach mains power cable to power supply and attach to power rail.
Connect DC Power Cable to DIN DC Input.



Figure 8: Mains power supply (854034)



WARNING

When mains power adapters are used, the equipment should be positioned so the mains plug will remain accessible for emergency disconnect.

Environmental DustTrak Battery Kit

(Optional Accessory P/N 854036)

See Quick Start Guide 6008712 included with accessory

The internal battery system consists of two rechargeable lead acid batteries with a specially designed charger. A wiring harness draws power from both batteries, doubling the run time. No connection through the outside of the enclosure is required for using the internal battery system. There is a 5.0AT 5x20mm fuse built in to the cable.



Figure 9: Battery kit (854036)

Notes

- To integrate the battery into the environmental enclosure, the battery will need to be purchased as an optional accessory. Part number 854036 includes: two (2) 22Ahr batteries; battery charger, battery tray, and dual wiring harness.

Additional battery (part number 801808).

Additional battery charger (part number 801809)

- Prior to using the Battery Pack for the first time, a full recharge is recommended. **Recharging Battery Pack(s) immediately after use (within one hour maximum) is critical to obtaining optimal recharge time, battery health, and battery life.**
- Use of components other than those specified by TSI may impair the safety features provided by the equipment.



WARNING

The instrument has been design to be used with batteries supplied by TSI. Do **not** use a substitute.

The TSI charger (P/N 801809) has been designed to be used with the battery packs supplied by TSI. Do **not** use a substitute charger to charge TSI battery packs.

Old batteries must be properly recycled in accordance with the local environmental regulations.

Alternate DC Power Sources

Solar Power System for Environmental DustTrak

(optional accessory P/N 854060)

See Quick Start Guide 6008416 included with accessory.



Figure 10: Solar power system (854060)

Heated Inlet Accessory

(optional accessory P/N 854041)

See Quick Start Guide 6008577 included with accessory.




Figure 11: Heated inlet accessory (854041)

Enclosure Heater

(optional accessory 854033)

See Quick Start Guide 6008412 included with accessory.




Figure 12: Enclosure Heater (854033)



WARNING

Ensure AC cable and all communication cables are routed away from direct contact with the heater module to prevent shorting and damage due to potential melted cable insulation.

Install Photometer inside Environmental Enclosure

1. Remove the Mounting Ring from bottom of inlet column and attach to top of photometer using four (4) screws provided.
Note: *Ensure keyhole opening is orientated to the front of the photometer.*
2. Add O-ring to mounting ring attached to photometer.
3. Lift photometer up through enclosure, guiding the attached mounting ring through the opening.
4. Place plastic glide ring around mounting ring protruding through top of enclosure.
5. Use the retainer ring to secure the photometer to the enclosure. Hand-tighten retainer ring to mounting ring. **Do not** use tools for additional leverage.




Figure 13: Install DustTrak Monitor – insert inlet ring up through opening



WARNINGS

- Retainer ring and O-ring must be properly orientated to ensure a good seal to prevent water leakage.
- Care must be taken to hold the photometer while tightening or loosening the retaining ring to prevent damage to the photometer from an unexpected drop.

Assembly and Installation of Inlet Column



Figure 14: Inlet column parts

1. Build inlet column starting from the bottom with the Inlet base or Heated Inlet sample conditioning module (optional accessory).
2. Set inlet column on top of mounted photometer, rotate slowly until alignment pin drops column into proper orientation.
3. Hand-tighten base retainer ring to secure inlet column to enclosure.
4. Slide retainer ring down to inlet base or optional heated inlet column.




Figure 15: Assembly and installation of inlet column

5. Add any optional size selective impactors (*not shown*). See Quick Start Guide 6008674 *Installing Impactor onto the Omni-directional inlet*.



Figure 16: Assembly and installation of inlet column

6. Add the water trap bottle.
7. Add the 360° omni-directional inlet.



WARNING

Inspect all O-rings for damage and contamination during installation to ensure a good seal to prevent water leakage.




Figure 17: Final configurations of inlet column



Figure 18: Removal of glass jar from flow stack



WARNING

Care must be taken when attaching or removing the omni-directional inlet column from the enclosure and/or photometer to prevent breaking the glass water trap jar due to mishandling or dropping the column.

Pole Mount Kit

(optional accessory 854031)

See Quick Guide 6008411 included with accessory.



Figure 19: Pole mount kit (854031)

Final Electrical Connection

After completing all internal connections from the Instrument and accessories to the DIN Rail, make final connection of DustTrak power connector to DIN Rail mounted power supply. Connect external power cord to the side of the enclosure and plug other end into an AC power outlet (DC solar power source will use 2-pin connector on left side of enclosure).




Figure 20: DustTrak Power Connection (*left*). Final connection to exterior AC power source (DC power source will use 2-pin connector on left side of enclosure – *right*)

- Line cord plug must be connected to electrical power inside a water resistant/waterproof outdoor receptacle enclosure.



Figure 21: Water resistant / waterproof outdoor receptacle enclosure

- Check instruments to verify power is working before closing and locking enclosure.



WARNING

Improper outdoor installation could result in equipment damage and/or electrical shock due to improper grounding. Installation must follow local electrical codes. Electrical connections should be completed by a licensed electrician.

(This page intentionally left blank)

Chapter 4

Operation

Overview

The Environmental Enclosure can be used in conjunction with the 8540, 8540-M, 8542-M, 8543, or 8543-M Environmental DustTrak aerosol monitor for many different applications. Its primary use is in outdoor applications to give the DustTrak monitor protection from the elements and the ability to sample efficiently in different wind speeds.

How to Properly Orient the Environmental Enclosure

Set up the Environmental Enclosure in a location where it can sample the particles of interest. It should be placed “out in the open,” away from obstructions which may affect wind currents. For example, do not place it at the corner of a building, which would cause swirling wind currents and result in poor particle sampling.

Use the Environmental Enclosure in wind conditions with speeds of 22 mph or less to obtain the most accurate readings. An increase in wind speed over 22 mph can decrease the sampling efficiency of the inlet to under the efficiency specified by PM₁₀ standards. If wind gusts of over 22 mph are present, the data collected is still valid, but be aware that the readings will be slightly lower than the actual mass concentration of aerosol present.

If the Environmental Enclosure is exposed to direct sunlight, causing the temperature inside to approach the operating limit of 50°C, the Solar Shield should be used. The Solar Shield blocks the direct sunlight, keeping the temperature inside the Environmental Enclosure cooler than it would otherwise be. Orient the Environmental Enclosure with Solar Shield such that the Solar Shield faces the sun directly when the sun is at its highest point in the sky. This will maximize the effectiveness of the Solar Shield.

Checklist for Sampling with the Environmental Enclosure

Before beginning a sample, check to see that all of the following conditions are satisfied:

- ✓ All components are properly installed into the enclosure as described in the Setup section.
- ✓ The Environmental DustTrak monitor (8540/8540-M/8542-M/8543/8543-M) has been zeroed at the temperature at which it will be sampling (if possible).
- ✓ The Environmental Enclosure has been put in a place clear of any obstructions that will affect the flow around the enclosure. The Enclosure is not resting directly on the ground (no standing water).
- ✓ The Environmental DustTrak monitor (8540/8540-M/8542-M/8543/8543-M) has been set to the appropriate survey or logging mode.
- ✓ The Enclosure is locked shut to prevent theft or vandalism to instrument.

Transporting the Environmental Enclosure

When transporting the Environmental Enclosure it is important to store its components correctly. To ensure that no damage is done to the enclosure or its components during transportation, the following steps should be taken:



Attention

The Environmental Enclosure is designed to protect equipment during stationary sampling only.

Do **not** transport or ship equipment inside the Environmental Enclosure.

1. Unscrew the aerosol inlet from the top of the case.
2. Empty any water from the water trap.
3. Remove antenna and extender for GSM/GPS modem accessory if in use.
4. Remove RH/Temp sensor for heated inlet accessory (if applicable).
5. Remove Environmental DustTrak aerosol monitor.
6. Remove batteries (if applicable).

7. Remove power supply (if applicable).
8. Remove Enclosure Heater (if applicable).
9. Package enclosure to prevent damage.
10. Package accessories to prevent damage.

Removing Photometer from Environmental Enclosure for Service or Replacement



WARNING

Disconnect all cables before removing photometer from Environmental Enclosure to prevent damage.

1. Unscrew the second knurled ring from the bottom.



Figure 22: Unscrew second knurled ring from bottom

2. Remove inlet assembly—either the Omni-directional Inlet or the Heated Inlet Assembly.
 - a. To remove an **Omni-directional Inlet**—loosen the knurled ring and lift the entire assembly out.



Figure 23: Remove inlet assembly

- b. To remove a **Heated Inlet Assembly**—the procedure is considerably more complicated. Follow the instructions below:
 - i. Inside the Enclosure, unlock and disconnect the Heated Inlet cable (note that the connector has the lock-release on the top back of the connector).



Figure 24: Disconnect heated inlet cable

- ii. Remove the Ferrite Clamp Assembly. Note that the clamp is released by inserting and twisting a small blade screwdriver. Also, for purposes of re-assembly, note that the cable twists two times through the Ferrite.



Figure 25: Removing ferrite clamp assembly

- iii. Carefully pull the Heated Inlet Assembly up while gently pulling the cable through the slotted opening.



Figure 26: Pull heated inlet assembly up

- iv. Carefully pull the Heated Inlet cable connector through the slot in the Mounting Ring. The Heated Inlet Assembly can then be completely removed.



Figure 27: Removing heated inlet assembly

3. Disconnect the USB Cable, Ethernet Cable, and Power Cable as shown.



Figure 28: Removing USB, Ethernet, and power cables

4. Disconnect the Temperature/Humidity Sensor Cable if you have a Heated Inlet.



Figure 29: Disconnecting temperature/humidity cable

5. Remove the knurled ring while supporting the Photometer. Then remove the Photometer from the Enclosure.



Figure 30: Removing photometer from enclosure

6. For photometers with a Heated Inlet, disconnect and remove the cables (as shown in the first two photographs). Then remove the Heated Inlet Controller (bottom photo)—the two highlighted screws use a 7/64" ball driver.



Figure 31: Removing cables and heated inlet controller

7. The Mounting Ring can be left attached or removed before shipment of the Photometer. If the Inlet Assembly needs to be re-attached to the Enclosure, the Mounting Ring must be removed. See the next section for instructions on reassembling the Inlet Assembly.



Figure 32: Mounting ring

Re-installing the Inlet Assembly

When the photometer is removed from the enclosure, the top of the enclosure will have an opening unless the Inlet Assembly is reinstalled. If the Enclosure is to be left outside, follow the steps below to re-install the Inlet-Assembly column to the mounting ring from the DustTrak monitor to ensure a waterproof seal on the enclosure.

1. Remove the mounting ring from the photometer. Save the four screws for reinstallation of the mounting ring on the photometer.




Figure 33: Remove mounting ring from photometer

2. Install the Mounting Ring from below into the top opening of the environmental enclosure. Install the Plastic Glide Ring on the bottom and then the knurled Retainer Ring. Tighten the Retainer Ring until tight.



Figure 34: Secure retainer ring



WARNINGS

- Retainer ring and O-ring must be properly orientated to ensure a good seal to prevent water leakage.
- Inspect all O-rings for damage and contamination during installation to ensure a good seal to prevent water leakage.

3. If you have a Heated Inlet Assembly, first feed the Temperature/Humidity Sensor cable through the slot in the Mounting Ring. Carefully feed the cable through the opening as you lower the Heater Inlet onto the Retaining Ring.



Figure 35: Heated Inlet cable

4. Note that the bottom of the Heated Inlet Assembly or Omni-directional Inlet has a “guide-hole” which must align with the alignment pin in the Mounting Ring. Rotate the Inlet Assembly back and forth until the hole aligns with the pin.



Figure 36: Aligning inlet assembly

5. Insert the Heated Inlet or Omni-directional Inlet fully. Firmly tighten the knurled ring of the Heated Inlet or Omni-directional Inlet. This completes the installation of the Heated Inlet or the Omni-directional Inlet assembly.



Figure 37: Secure inlet column to retainer ring

(This page intentionally left blank)

Chapter 5

Maintenance

Annual Maintenance Checks

Note:

Extreme conditions may require more frequent maintenance.

1. Check the gasket around the door for proper seal.
2. Check the door vents for tightness and filters in place.
3. Ensure the photometer is secured to the enclosure with the retainer ring.
4. Ensure the Omni-directional inlet column is secured to the photometer by the column retainer ring.
5. Empty the water trap if needed.
6. Open the Impactor (if used) to clean and re-oil the Impactor.
7. Ensure all cable grommets and whole plugs through environmental enclosure are snug and weather tight.
8. Ensure all internal wiring and cable routing tie wraps are properly secured to the enclosure.
9. Inspect internal wiring and cables for loose connections and damaged wires and cables.
10. Ensure wires and cables are not routed on top of heater at risk of melting (if used).
11. Ensure enclosure is securely mounted to Pole Mounting Kit or other fixture and any attachment point.
12. Ensure enclosure is securely locked to prevent theft.

Cleaning the Aerosol Inlet

Under normal operating conditions, the external aerosol inlet will remain clean and unobstructed. Under very dirty conditions; however, the inlet may become obstructed with vegetative debris or insects. To ensure the inside of the aerosol inlet is clean, periodically remove Omni-directional inlet and blow compressed air through the bottom of the inlet.



Caution

Do not disassemble the Environmental Enclosure aerosol inlet for any reason. It is **not** designed for field service and reassembly.

Emptying the Water Trap

If any water or moisture has accumulated in the water trap, unscrew the water trap from the Omni-directional inlet and empty it.

The bottle must be securely hand tightened to seal against the O-ring to prevent leaking. Make sure the tightly secured bottle is oriented in the position shown in Figure 38.

If water trap top is removed from fitting, re-apply Teflon[®] pipe tape to fitting before installing cap to ensure a good seal is maintained.




Figure 38: Water trap O-ring and Orientation on inlet column

Cleaning and Oiling Impactors

Follow the recommended Impactor cleaning interval for size selective Impactors used with Models 8540, 8540-M, and 8542-M Environmental DustTrak instruments shown below.

Recommended impactor maintenance interval is every two months except where the 'average dust concentration' level indicated in the table shows the impactor should be cleaned more frequently:

Average dust concentration (mg/m ³)	Impactor maintenance interval
0.015	97 days
0.025	60 days
0.035	42 days
0.050	30 days
0.100	16 days
0.150	10 days
0.250	6 days
0.400	4 days

1. Unscrew Impactor. Check O-ring on the Impactor base.
2. Clean outside and inside of Impactor and the Impactor plate using a clean brush and a light solvent. Dry impactor parts by blowing it out with compressed air, or let it air-dry thoroughly.
3. Apply two drops of oil (included) to the impactor plate. Do **not** over-fill impaction plate.



Figure 39: Apply 2 Drops of Oil to Impactor Plate

4. Screw (hand-tighten) impactor back together.

(This page intentionally left blank)

Chapter 6

Troubleshooting the Environmental Enclosure

The table below lists the symptoms, possible causes and recommended solutions for common problems encountered with the Environmental DustTrak Enclosure.

Possible Cause	Corrective Action
Photometer does not turn on.	
Bad Power Connection	Check all power connections from the outside of the Enclosure to the Photometer. If a battery is used, check the connection to the batteries.
Readings are unusually low.	
Zero was not checked on DustTrak monitor.	Re-zero DustTrak monitor at desired sampling conditions.
Plugged external inlet.	Remove inlet from the Enclosure; blow out debris with compressed air. Rinse with clean air, if needed. DO NOT DISASSEMBLE COVER ON INLET ASSEMBLY. Take off water trap bottle and clean all exposed surfaces.
Sampling in wind speeds over 22 mph.	DustTrak monitor will under-sample slightly in high wind speeds. No correction possible.
Enclosure located near an object that obstructs the flow.	Move the Environmental Enclosure into a more open area.
Leak in the inlet.	Make sure the upper inlet assembly and the water trap are screwed in tightly. Make sure tubing is secured on the enclosure barb and the DustTrak monitor. Make sure inlet assembly O-ring is in place.

(This page intentionally left blank)

Appendix A

Specifications

Specifications are subject to change without notice.

Environment Enclosure

Sampling Conditions	
Wind Speed	0 to 22 mph (0 to 36 kph)
Operating Temperature	32 to 120°F (0 to 50°C)
Operating Temperature with Heater accessory Model 854034	-4 to 120°F (-20 to 50°C)
Storage Temperature	-4 to 140°F (-20 to 60°C)
Ingress Protection	IP44 IP54 with vent plugs installed (TSI 6008622)
Physical	
External dimensions with no sample inlet (HWD)	16 x 12 x 12.25 in. (411 x 305 x 311 mm)
Approximate Weight	Enclosure (empty) 20 lbs (9.07 kg)
Approximate weight of accessories	Environmental DustTrak..... 5.3 lbs (2.4 kg) Thiamis Node Kit..... 0.8 lbs (0.4 kg) Internal Battery Kit 30 lbs (13.6 kg) Heated Inlet Sample Conditioner..... 2.0 lbs (0.9 kg) Enclosure Heater Kit 3.4 lbs (1.54 kg) Omnidir. inlet w/water jar..... 2.2 lbs (1.0 kg) Impactor 0.23 lbs (.105 kg) Power Supply..... 1.7 lbs (0.8 kg) Solar shield 2.0 lbs (0.9 kg) Handle kit..... 0.6 lbs (0.3 kg) Pole Mount Kit..... 6.7 lbs (3.0 kg) Lufft WS300 1.8 lbs (0.8 kg) Lufft WS500 2.9 lbs (1.3 kg)

Maintenance Requirement				
Maintenance Check/ Clean omni-directional inlet	Average Dust Concentrations			
	35 µg/m ³	50 µg/m ³	100 µg/m ³	
	42 days	30 days	16 days	
Internal Battery System				
Battery Run-time	Environmental DustTrak/DRX Photometer:			
	Single battery..... 21 to 24 hours (typical)			
	Dual batteries 42 to 48 hours (typical)			
	Environmental DustTrak/DRX Photometer (with heated inlet accessory):			
	Single Battery 15 hours (typical)			
	Dual Batteries 30 hours (typical)			
Battery Charge Time	8 to 9 hours at 72°F (22°C) (New battery, deep discharge to 95% charge)			
AC and DC Power Requirements				
AC Power	100 to 240 VAC, 50/60 Hz, 120 W Maximum (300 W Max for power supply included with Enclosure Heater)			
DC Power (solar option)	12 VDC, 50 W Maximum			



UNDERSTANDING, ACCELERATED

TSI Incorporated – Visit our website www.tsi.com for more information.

USA Tel: +1 800 874 2811

India Tel: +91 80 67877200

UK Tel: +44 149 4 459200

China Tel: +86 10 8219 7688

France Tel: +33 1 41 19 21 99

Singapore Tel: +65 6595 6388

Germany Tel: +49 241 523030

P/N 6008410 Rev. F

©2016 TSI Incorporated

Printed in U.S.A.





Distributed by:

Kenelec Scientific Pty Ltd
1300 73 22 33
sales@kenelec.com.au
www.kenelec.com.au